



**No. d'art.: YMOCA-CASADIMM**  
**Casa Trailing Edge Dimmer Bluetooth control module,**  
**max. 150W LED / 200W ohmic, IP20**

**NEWS!**



The CASA trailing edge dimmer is a trailing edge dimmer. Its use enables stepless dimming of trailing-edge lamps. Output power 150W LED / 200W ohmic (e.g. light bulbs). It is controlled wirelessly with the CASAMBI® app. Strain relief and terminal cover are integrated.

**DONNÉES TECHNIQUES**

Données électriques	
Tension d'entrée AC	AC 220-240V / 50-60Hz
Consommation en veille	0,5 W
Puissance de sortie max	150 W
Coupe transversale	2,5 mm <sup>2</sup>
Types de charges	Charge capacitive
Type de communication	Sans fil, Casambi
Mode de gradation	TRIAC
Bande de fréquence	2,403 - 2,479 GHz
max. Transmettre la puissance	+4 dBm
CASAMBI Inside	Oui
Tests d'acceptation	
Certificats	CE
Classe de protection	II
Degré de protection (IP)	IP 20
Température ambiante	-20 à +50 C°
Température du boîtier max.	60 C°



Données physiques	
Matériau du boîtier	Plastique
Couleur du boîtier	blanc
Dimensions du produit longueur	143 mm
Dimensions du produit largeur	47 mm
Dimensions du produit hauteur	29 mm
Longueur d'emballage	162 mm
Largeur d'emballage	51 mm
Hauteur d'emballage	31 mm