



No. d'art.: YMOCA-PWM-05
CASA PWM5 Bluetooth control module,

NEWS!

The CASA PWM5 unit enables direct access to the preconfigured functions of the CASAMBI® lighting control. These are on the one hand dimming, switching lights on and off and on the other hand setting colors. By integrating the fifth channel, RGB CCT is now possible. 5 channels, output voltage 12-24V DC. Strain relief and terminal cover are integrated. Connected lights remain flicker-free down to low dimming levels.



DONNÉES TECHNIQUES

Données électriques	
Tension d'entrée DC	12 V
max. tension d'entrée DC	24 V
Consommation en veille	0,4 W
Puissance de sortie max	170 W
Tension de sortie DC max	24 V
Coupe transversale	1,5 mm ²
Type de communication	Bluetooth
Mode de gradation	PWM
Exécution électriquement	avec alimentation externe
Bande de fréquence	2,403 - 2,479 GHz
max. Transmettre la puissance	+4 dBm
CASAMBI Inside	Oui
Tests d'acceptation	
Certificats	CE
Degré de protection (IP)	IP 20
Température ambiante	-20 à +40 C°
Température du boîtier max.	60 C°



Données physiques	
Matériau du boîtier	Plastique
Couleur du boîtier	blanc
Dimensions du produit longueur	143 mm
Dimensions du produit largeur	47 mm
Dimensions du produit hauteur	29 mm
Longueur d'emballage	162 mm
Largeur d'emballage	51 mm
Hauteur d'emballage	31 mm